

# hp SignagePlayer mp8000

Get noticed

Built for digital signage, this powerful media player with Scala® QuickStart™ software produces communications to capture customers attention.



## Capture attention

It's not enough to just put your message out there. You've got to get noticed. HP SignagePlayer mp8000 series is the technology you need to capture your customer's attention and create memorable impressions. Use the HP SignagePlayer mp8000 to help increase sales and improve the effectiveness your communications. As part of a full digital signage solution from HP, HP SignagePlayer mp8000 helps provide information in an attractive format that entertains, informs and engages for a unique customer experience that gets results.

## Built for digital signage

Preinstalled with Microsoft® Windows® Embedded Standard 2009 operating system and Scala® QuickStart™ software, HP SignagePlayer mp8000 is designed for smooth and reliable operation in demanding digital signage applications. Scala® QuickStart™ digital signage deployment software<sup>1</sup> makes creating professional looking messages quick and easy. Just use Scala® QuickStart™ to create relevant messages, push the information to your HP Digital Signage Displays in brilliant color, and grab your customer's attention.

Choose the form factor that is right for your environment. The ultra-slim HP SignagePlayer mp8000s can be mounted behind your HP Digital Signage Display<sup>2</sup>. Or, choose the HP mp8000r for performance and versatility. HP

SignagePlayer mp8000 is specifically optimized for digital signage media and built for demanding digital signage duty cycles.

## Engage customers

Grab attention with relevant messages and information which help your customer connect with your business, increasing customer satisfaction. Create, update, maintain and monitor content and devices across networks of digital signs, delivering the right message to the right people at the right time<sup>1</sup>. Manage your data, customer information, and messages on HP SignagePlayers as your business and customer needs change.

## Complete signage solutions

Our relationship with leading digital signage software makers allows you to take advantage of integrated software to seamlessly create and manage your information. No IT manager, no problem. Built in management tools help you securely manage and monitor your information even when the sign is powered off.

HP Digital Signage Solutions are built for demanding 24/7 use so you can focus on your business not your technology. For more information about HP SignagePlayer mp8000 or HP Digital Signage Solutions visit us at [www.hp.com/go/digitalsignage](http://www.hp.com/go/digitalsignage).



# SignagePlayer mp8000

SPECIFICATIONS	mp8000s	mp8000r
<b>Form factor</b>	Ultra-slim Desktop	Small Form Factor
<b>Operating system</b>	Pre-installed Genuine Windows® Embedded Standard 2009	
<b>Software</b>	Scala® QuickStart™	
<b>Processor<sup>3</sup></b>	Intel® Core 2™ Duo 8400 processor	
<b>Chipset</b>	Intel® Q45 Express	
<b>Memory</b>	2 GB standard; Two (2) SODIMM slots	2 GB standard; Four (4) DIMM slots
<b>Internal Storage<sup>4</sup></b>	160 GB 2.5" Hard Disk Drive	320 GB 3.5" Hard Disk Drive
<b>Expansion bays</b>	External: One (1) Slimline Internal: One (1) 2.5-inch	External: One (1) 3.5-inch One (1) 5.25-inch Internal: One (1) 3.5-inch
<b>Expansion slots</b>	One (1) mini PCIe	One (1) low profile PCI Two (2) low profile PCIe x1 One (1) low profile PCIe x16
<b>Graphics</b>	Integrated Intel® Graphics Media Accelerator 4500	NVIDIA GeForce 310
<b>Audio/Visual</b>	Realtek ALC261 HD Audio, internal speaker	
<b>Communications<sup>5</sup></b>	Intel 82567LM Gigabit Network Connection Intel Wi-Fi Link 5100 a/b/g/n Wireless NIC	HP 802.11 b/g/n Wireless NIC
<b>Ports and Connectors</b>	Front: four (4) USB, microphone, headphone Rear: six (6) USB, PS/2 keyboard and mouse, line in, line out, VGA, DisplayPort, RJ-45 Network	Front: four (4) USB, microphone, headphone Rear: six (6) USB, PS/2 keyboard and mouse, line in, line out, VGA, DisplayPort, RJ-45 Network, one (1) serial, second serial port and a parallel port available as an option
<b>Input devices</b>	HP USB Standard Keyboard, HP USB optical scroll mouse	
<b>Security</b>	Trusted Platform Module (TPM) 1.2, DriveLock, Solenoid Hood Lock and sensor, Chassis padlock loop and cable lock support	
<b>Power</b>	135W 87% efficient active PFC  Advanced Configuration and Power Management Interface (ACPI), Dual State Power Button	240W active PFC 240W 89% efficient active PFC
<b>Dimensions</b>	66 x 251.5 x 254 mm 2.6 x 9.9 x 10 in	100 x 338 x 378.5 mm 3.95 x 13.30 x 14.9 in
<b>Weight</b>	3.07 kg 6.75 lb	7.6 kg 16.72 lb
<b>Warranty and services<sup>6</sup></b>	3-3-3 limited warranty delivers on-site, next business-day service for parts and labor and includes free telephone support 24 x 7; other HP Care Pack Services available see <a href="http://www.hp.com/go/lookuptool">http://www.hp.com/go/lookuptool</a>	



# SignagePlayer mp8000



HP SignagePlayer mp8000s mounted to the HP LD200 digital signage display. Optional HP Digital Signage Display and Wall Mount Kit sold separately.

## SignagePlayer mp8000s



Built-in Scala® QuickStart™ player



## SignagePlayer mp8000r





## SignagePlayer mp8000

1. Content management software available via monthly subscription to Scala Quickstart.
2. HP Digital Signage Display sold separately. HP Wall Mount Kit required and sold separately.
3. 64-bit computing on Intel architecture requires a computer system with a processor, chipset, BIOS, operating system, device drivers and applications enabled for Intel® 64architecture. Processors will not operate (including 32-bit operation) without an Intel 64 architecture-enabled BIOS. Performance will vary depending on your hardware and software configurations. See [www.intel.com/info/em64t](http://www.intel.com/info/em64t) for more information. Dual/Quad Core is designed to improve performance of certain software products. Not all customers will necessarily benefit from the use of this technology. Intel's numbering is not a measurement of higher performance.
4. For hard drives, GB = 1 billion bytes. Actual formatted capacity is less. Up to 8GB (for XP and XP Pro), up to 10 GB (for Vista) and up to 16 GB (for Windows 7) of disk space is reserved for the system recovery software.
5. Wireless access point and Internet service required and sold separately.
6. Service levels and response times for HP Care Packs may vary depending on geographic location. Restrictions and limitations apply. Service starts at date of hardware purchase. For details, visit [www.hp.com/go/carepack](http://www.hp.com/go/carepack).

# Legacy Technology Services

**We Rent & Sell All Types Of Barcode Equipment**

Call now to talk to an expert

**866-271-9891**

[www.LegacyGlobal.com](http://www.LegacyGlobal.com)

Some brands we carry



MOTOROLA

**Intermec**

**DATALOGIC™**

**Honeywell**

**EQUINOX**  
PAYMENTS



## About us

- Legacy Technology Services is a leading nationwide provider of mobile computing, barcode, printers and point of sale equipment and services.
- For over a decade, thousands of clients across North America have trusted us to provide equipment from leading manufacturers backed by the services to support them.

## Latest Hardware from top manufacturers

- Legacy handles virtually every major manufacturer of mobile computing, barcoding and point of sale equipment.

## Expert Repair and Maintenance services

- Legacy is one of the best repair facilities in North America

## Discontinued product sourcing

- They don't make it anymore? Our inventory also includes manufacturer close-outs and discontinued equipment to support our clients legacy infrastructure.

## Trade-in and Disposal services

- That old equipment laying around your facility may still have some value. Legacy routinely purchases equipment from our clients around the globe.
  - Data destruction
  - Hardware disposal
  - Auditing services

## Dedicated client account team

- Dedicated, highly trained account managers are here to answer all your questions and provide top notch service.

## Equipment rental services

- Sometimes renting is a better solution, Legacy's huge rental inventory provides the equipment you need for temporary needs and projects.



[Legacy, Inc.](http://Legacy, Inc.)

160 West Road,  
Ellington, CT 06029

Toll Free: 866-271-9891

Fax: 888-522-4684